

## Message Flow Details

### MM00036 - Confirmation or Rejection of Energisation Status Change


#### Market Message Information

<b>Market Message Reference</b>	MM00036
<b>MM Description</b>	This flow confirms that the Energisation Status of a metering point has been changed, or notifies that a change was not possible and gives the reason for failure.
<b>Local Catalogue Reference</b>	D0139
<b>Version</b>	002
<b>Notes</b>	Where an AMVLP (Asset Metering Virtual Lead Party) is involved, the MPAN Core must contain an AMSID (Asset Metering System Identifier) and not an MPAN


#### Scenario Variants

<b>Scenario Variant</b>	<b>Name</b>	<b>Source</b>	<b>Target</b>	<b>Owner</b>	<b>Api Route</b>	<b>Api Method</b>
SV00036	Confirmation or Rejection of Energisation	Distribution Network Operator	Electricity Meter Equipment Manager	Retail Energy Code Company		

	Status Change					
SV00037	Confirmation or Rejection of Energisation Status Change	Distribution Network Operator	Electricity Supplier	Retail Energy Code Company		
SV00038	Confirmation or Rejection of Energisation Status Change	Electricity Meter Equipment Manager	Distribution Network Operator	Retail Energy Code Company		
SV00039	Confirmation or Rejection of Energisation Status Change	Electricity Meter Equipment Manager	Half Hourly Data Collector	Retail Energy Code Company		
SV00040	Confirmation or Rejection of Energisation Status Change	Electricity Meter Equipment Manager	Non Half Hourly Data Collector	Retail Energy Code Company		
SV00041	Confirmation or Rejection of	Electricity Meter	Electricity Supplier	Retail Energy		



	Energisation Status Change	Equipment Manager		Code Company		
SV00461	Confirmation or Rejection of Energisation Status Change	Electricity Meter Equipment Manager	Asset Metering Virtual Lead Party	Retail Energy Code Company		
<a href="#">SVxxxxx</a>	<a href="#">Confirmation or Rejection of Energisation Status Change</a>	<a href="#">Distribution Network Operator</a>	<a href="#">Electricity Smart Meter Equipment Manager</a>	<a href="#">Retail Energy Code Company</a>		
<a href="#">SVxxxxx</a>	<a href="#">Confirmation or Rejection of Energisation Status Change</a>	<a href="#">Electricity Smart Meter Equipment Manager</a>	<a href="#">Electricity Supplier</a>	<a href="#">Retail Energy Code Company</a>		
<a href="#">SVxxxxx</a>	<a href="#">Confirmation or Rejection of Energisation Status Change</a>	<a href="#">Distribution Network Operator</a>	<a href="#">Electricity Advanced Meter Equipment Manager</a>	<a href="#">Retail Energy Code Company</a>		
<a href="#">SVxxxxx</a>	<a href="#">Confirmation or Rejection</a>	<a href="#">Electricity Advanced</a>	<a href="#">Electricity Supplier</a>	<a href="#">Retail Energy</a>		




	<a href="#">of Energisation Status Change</a>	<a href="#">Meter Equipment Manager</a>		<a href="#">Code Company</a>		
<a href="#">SVxxxxx</a>	<a href="#">Confirmation or Rejection of Energisation Status Change</a>	<a href="#">Electricity Advanced Meter Equipment Manager</a>	<a href="#">Asset Metering Virtual Lead Party</a>	<a href="#">Retail Energy Code Company</a>		

### **Data Items**

<b>Data Item Number</b>	<b>Local Catalogue Reference</b>	<b>Name</b>
<a href="#">DI50003</a>	J0003	MPAN Core
<a href="#">DI50004</a>	J0004	Meter Id (Serial Number)
<a href="#">DI50007</a>	J0010	Meter Register Id
<a href="#">DI50009</a>	J0014	Date of Action
<a href="#">DI50016</a>	J0024	Site Visit Check Code
<a href="#">DI50019</a>	J0040	Register Reading
<a href="#">DI50041</a>	J0080	Energisation Status
<a href="#">DI50097</a>	J0171	Reading Type
<a href="#">DI50623</a>	J1253	Failure to Energise or De-Energise Reason Code

### **Flow Structure**

#### **MM00036 - Confirmation or Rejection of Energisation Status Change - Message Structure**



Group ID	Group Description	Range	Condition	L1	L2	L3	L4	L5	L6	L7	L8	Data Item Name	Data Item Rule
261	MPAN Cores	1-*		G									
					1							<a href="#">MPAN Core</a>	
					1							<a href="#">Energisation Status</a>	
					1							<a href="#">Date of Action</a>	
					0							<a href="#">Failure to Energise or De-Energise Reason Code</a>	
					0							<a href="#">Site Visit Check Code</a>	
262	Meter Detail per MPAN Core	0-*		G									
						1						<a href="#">Meter Id (Serial Number)</a>	
263	Register Details per Meter	0-*				G							
							1					<a href="#">Meter Register Id</a>	<a href="#">For MHHS Metering Points, this Data Item should be populated with the Cumulative Register Reading for Smart</a>

Commented [SJ1]: IR7 Update - to reflect agreed definitions within Schedule 1

