### Message Flow Details

# MM00140 - Revenue Protection Report on Action Taken

# Market Message Information

Market Message Reference	MM00140					
MM Description	A report by the Revenue Protection Service on the outcome of an investigation.					
Local Catalogue Reference	D0239					
Version	001					
Notes	For those investigations where revenue recovery has been pursued, a detailed report will be submitted to the Supplier. Though all of the address data items included in this flow are defined within the structure as being optional, the address itself is mandatory and must be included in the flow. The use of any individual address item cannot be made mandatory as, in the absence of an agreed address structure for all flows, an address may be constructed from any combination of the Address Line and Postcode items. Where the Meter Operator is informed via this flow the Meter Operator Informed Indicator should always be set to T (Meter Operator Informed)					

## Scenario Variants

Scenario Variant	Name	Source	Target	Owner	Api Route	Api Method
SV00140		Protection Service	, Meter Equipment	Retail Energy Code Company		

SV00141	Revenue Protection Report on Action Taken	Revenue Protection Service	Electricity Supplier	Retail Energy Code Company	
<u>SVxxxxx</u>	<u>Revenue</u> <u>Protection</u> <u>Report on</u> <u>Action</u> <u>Taken</u>	<u>Revenue</u> Protection Service	<u>Electricity</u> <u>Smart</u> <u>Meter</u> Equipment <u>Manager</u>	<u>Retail</u> <u>Energy</u> <u>Code</u> Company	
<u>SVxxxxx</u>	Revenue Protection Report on Action Taken	<u>Revenue</u> Protection Service	<u>Electricity</u> Advanced <u>Meter</u> Equipment Manager	<u>Retail</u> <u>Energy</u> <u>Code</u> Company	

### Flow Structure

# MM00140 - Revenue Protection Report on Action Taken - Message Structure

	Group Description	Range	Condition	L1	L2	L3	L4	L5	L6	L7	L8	Data Item Name	Data Item Rule
632	Investigation Details		- Please reference Address Population Guidance v1.0.	G									
					1							MPAN Core	
					0							Customer Name	
					0							<u>Metering Point</u> Address Line 1	
					0							Metering Point Address Line 2	
					0							Metering Point Address Line 3	
					0							Metering Point Address Line 4	

			0				Metering Point Address Line 5
			0				Metering Point Address Line 6
			0				Metering Point Address Line 7
			0				Metering Point Address Line 8
			0				Metering Point Address Line 9
			0				Metering Point Postcode
			1				Revenue Protection Priority Level
633	Original Meter Details	1-*	G				
				1			<u>Meter Id (Serial</u> <u>Number)</u>
				1			Energisation Status
				1			Meter Action Code
				1			Irregularity Confirmed Indicator
				0			Revenue Recovery Indicator
634	Meter Register Detail per Meter	1-*		G			
					1		Meter Register Id
					1		Reading Date & Time

						1			Register Reading
635	Changed Meter Details	0-1	Changed Meter Details message collection is Mandatory if Meter Action Code value is 01; or the message collection is Not Present if any other value.		G				
						1			<u>Meter Id (Serial</u> <u>Number)</u>
						1			Energisation Status
						1			Meter Operator Informed Indicator
						0			Additional Information
636	Meter Register Detail per Meter	1-*				G			
							1		Meter Register Id
							1		Reading Date & Time
							1	_	Register Reading