Message Flow Details

MM00092 - Confirmation of Token Meter Installation

Market Message Information

Market Message Reference	MM00092
MM Description	Confirmation of token meter installation is being given with details of the meter and settings.
Local Catalogue Reference	D0178
Version	001
Notes	Standard tariff details will be contained within Service Level Agreements between the parties. Emergency Credit and Fixed Charge values will only be given when an override has been applied. Though all of the address data items included in this flow are defined within the structure as being optional, the address itself is mandatory and must be included in the flow. The use of any individual address item cannot be made mandatory as, in the absence of an agreed address structure for all flows, an address may be constructed from any combination of the Address Line and Postcode items.

Scenario Variants

Scenario Variant	Name	Source	Target	Owner	Api Route	Api Method
SV00092	Meter	Electricity Meter Equipment Manager	Electricity	Retail Energy Code Company		
<u>SVxxxxx</u>	Confirmation of Token Meter Installation	Electricity Smart Meter Equipment Manager	Electricity Supplier	Retail Energy Code Company		

Flow Structure

MM00092 - Confirmation of Token Meter Installation - Message Structure

Group ID	Group Description	Range	Condition	L1	L2	L3	L4	L5	L6	L7	L8	Data Item Name	Data Item Rule
365	MPAN Cores	1-*	- Please reference Address Population Guidance v1.0.	G									
					1							MPAN Core	
					1							Energisation Status	
					0							Customer Name	
					0							Metering Point Address Line 1	
					0							Metering Point Address Line 2	
					0							Metering Point Address Line 3	
					0							Metering Point Address Line 4	
					0							Metering Point Address Line 5	
					O							Metering Point Address Line 6	
					O							Metering Point Address Line 7	
					0							Metering Point Address Line 8	
					0							Metering Point Address Line 9	
					0							Metering Point Postcode	

				О				Additional Information
				1				Tariff Code
366	Meter Details per MPAN Core			G				
					1			Meter Id (Serial Number)
					1			Meter Location
					1			Manufacturers Make & Type
					1			Meter Current Rating
					1			Supply Voltage
					1			Number of Phases
					1			Date of Meter Installation
					1			Service Reference
					1			Service Level Reference
					1			Total Debt
					1			Debt Recovery Rate
					О			Emergency Credit
					О			Standing Charge
					1			Initial Credit
367	Register Details per Meter	1-*			G			
						1		Meter Register Id
						1		Meter Register Type

			1			Number of Register Digits	
			1			Register Reading	